

M E L
B Y
E

RAYCORE

Q3-S182 V3.2E

Specification of SFP Copper-RJ45 1.25G Transceiver

Part Number: ATRG-Cx00-SC0xx-xx



Raycore's Copper Small Form Pluggable (SFP) transceivers is high performance, cost effective module compliant with the Gigabit Ethernet and 1000- BASE-T standards as specified in IEEE 802. 3-2002 and IEEE 802.3ab, which supporting 1000Mbps data- rate up to 100 meters reach over unshielded twisted-pair category 5 cable. The module supports 1000 Mbps full duplex data-links with 5-level Pulse Amplitude Modulation (PAM) signals. All four pairs in the cable are used with symbol rate at 250Mbps on each pair. The module provides standard serial ID information compliant with SFP MSA, which can be accessed with address of A0h via the 2 wire serial CMOS EEPROM protocol. The physical IC can also be accessed via 2wire serial bus at address A0h.

Features

- Up to 1.25Gb/s bi-directional data links
- Hot-pluggable SFP footprint
- TX Disable and RX with LOS/ without LOS function
- Extended case temperature range (0°C to +70°C)
- Fully metallic enclosure for low EMI
- Low power dissipation (1.05 W typical)
- Compact RJ-45 connector assembly
- Access to physical layer IC via 2-wire serial bus
- 1000 BASE-T operation in host systems with SERDES interface
- 10/100/1000Mbps compliant in host systems with SGMII interface

Applications

- 1.25 Gigabit Ethernet over Cat 5 cable



Specifications

+3.3V Volt Electrical Power Interface

The Copper SFP has an input voltage range of +5V +/- 5%. The 3.3V maximum voltage is not allowed for continuous operation.

+3.3V volt Electrical Power Interface						
Parameter	Symbol	Min	Typ	Max	Units	Notes/Conditions
Supply Current	I _s		320	375	mA	1.2W max power over full range of voltage and temperature. See caution note below
Input Voltage	V _{cc}	3.13	3.3	3.47	V	Referenced to GND
Maximum Voltage	V _{max}			4	V	
Surge Current	I _{surge}			30	mA	Hot plug above steady state current. See caution note below

Caution: Power consumption and surge current are higher than the specified values in the SFP MSA

Low-Speed Signals

MOD_DEF (1) (SCL) and MOD_DEF (2) (SDA) are open drain CMOS signals (see section VII, "Serial Communication Protocol"). Both MOD_DEF (1) and MOD_DEF (2) must be pulled up to V_{CC}_{HOST}.

Low-Speed Signals, Electronic Characteristics					
Parameter	Symbol	Min	Max	Units	Notes/Conditions
SFP Output LOW	V _{OL}	0	0.5	V	4.7k to 10k pull-up to V _{CC} _{HOST} , measured at host side of connector
SFP Output HIGH	V _{OH}	V _{CC} _{HOST} - 0.5	V _{CC} _{HOST} + 0.3	V	4.7k to 10k pull-up to V _{CC} _{HOST} , measured at host side of connector
SFP Input LOW	V _{IL}	0	0.8	V	4.7k to 10k pull-up to V _{CC} , measured at SFP side of connector
SFP Input HIGH	V _{IH}	2	V _{CC} + 0.3	V	4.7k to 10k pull-up to V _{CC} , measured at SFP side of connector



High-Speed Electrical Interface

All high-speed signals are AC-coupled internally.

High-Speed Electrical Interface Transmission Line-SFP						
Parameter	Symbol	Min	Typ	Max	Units	Notes/Conditions
Line Frequency	fL		125		MHz	5-level encoding, per IEEE 802.3
TX Output Impedance	Zout,TX		100		Ohm	Differential, for all Frequencies between 1MHz and 125MHz
RX Input Impedance	Zin,RX		100		Ohm	Differential, for all Frequencies between 1MHz and 125MHz

High-speed electrical interface, host-SFP

High-Speed Electrical Interface, Host-SFP						
Parameter	Symbol	Min	Typ	Max	Units	Notes/Conditions
Single ended data input swing	Vinsing	250		1200	mV	Single ended
Single ended data output swing	Voutsing	350		800	mV	Single ended
Rise/Fall Time	Tr,Tf		175		psec	20%-80%
TX Input Impedance	Zin		50		Ohm	Single ended
RX Output Impedance	Zout		50		Ohm	Single ended

General Specifications

General						
Parameter	Symbol	Min	Typ	Max	Units	Notes/Conditions
Data Rate	BR	10		1,000	Mb/sec	IEEE 802.3 compatible. See Notes 2 through 4 below
Cable Length	L			100	m	Category 5 UTP. BER <10 ⁻¹²

Notes:

1. Clock tolerance is +/- 50 ppm
2. By default, the RC-GP6R0xHA is a full duplex device in preferred master mode
3. Automatic crossover detection is enabled. External crossover cable is not required




Environmental Specifications

Environmental Specifications						
Parameter	Symbol	Min	Typ	Max	Units	Notes/Conditions
Operating Temperature	Top	0		70	°C	Refer to Ordering information
		-40		85		
Storage Temperature	Tsto	-40		85	°C	Ambient temperature

References

1. Gigabit Interface Converter (SFP) Transceiver Multi-Source Agreement (MSA),
2. IEEE Std 802.3, 2002 Edition. IEEE Standards Department, 2002.
3. "AT24C01A/02/04/08/16 2-Wire Serial CMOS E2PROM", Atmel Corporation.
4. "Alaska Ultra 88E1111 Integrated 10/100/1000 Gigabit Ethernet Transceiver", Marvell Corporation.

Pin Definitions



Pin Descriptions

Pin	Signal Name	Description	Plug Seq.	Notes
1	V _{EET}	Transmitter Ground	1	
2	TX FAULT	Transmitter Fault Indication	3	Note1
3	TX DISABLE	Transmitter Disable	3	Note2
4	MOD_DEF(2)	SDA Serial Data Signal	3	Note3
5	MOD_DEF(1)	SCL Serial Clock Signal	3	Note3
6	MOD_DEF(0)	TTL Low	3	Note3
7	Rate Select	Not Connected	3	
8	LOS	Loss of Signal	3	Note4
9	V _{EER}	Receiver ground	1	
10	V _{EER}	Receiver ground	1	
11	V _{EER}	Receiver ground	1	
12	RX-	Inv. Received Data Out	3	Note 5
13	RX+	Received Data Out	3	Note 5
14	V _{EER}	Receiver ground	1	
15	V _{CCR}	Receiver Power Supply	2	
16	V _{CCT}	Transmitter Power Supply	2	
17	V _{EET}	Transmitter Ground	1	
18	TX+	Transmit Data In	3	Note 6
19	TX-	Inv. Transmit Data In	3	Note 6
20	V _{EET}	Transmitter Ground	1	

Notes:

Plug Seq.: Pin engagement sequence during hot plugging.

1. TX Fault is not supported and is always connected to ground.
2. TX disable, an input used to reset the transceiver module. This pin is pulled up within the module with a 4.7kohms resistor.

Low (0 – 0.8 V): Transceiver on

Between (0.8 V and 2.0 V): Undefined

High (2.0 – 3.465 V): Transceiver in reset state

Open: Transceiver in reset state

3. Mod-Def 0, 1, 2. These are the module definition pins. They should be pulled up with a 4.7K~10K resistor on the host board. The pull-up voltage shall be V_{ccT} or V_{ccR}

Mod-Def 0 is grounded by the module to indicate that the module is present

Mod-Def 1 is the clock line of two wire serial interface for serial ID

Mod-Def 2 is the data line of two wire serial interface for serial ID

4. RX_LOS (Loss of Signal): LVTTTL compatible with a maximum voltage of 2.5V. RX_LOS can enabled or disabled (Refer to Ordering information), RX_LOS is not used and is always tied to ground via 100-ohm resistor.
5. RD-/+ : These are the differential receiver outputs. They are AC coupled 100 differential lines which should be terminated with 100 (differential) at the user SERDES.
6. TD-/+ : These are the differential transmitter inputs. They are AC-coupled, differential lines with 100 differential termination inside the module.



M E L
B Y
E

Ordering information

Part Number	Specification Description
ATRG-CG00-SC0LS-xx	Copper SFP 10/100/1000Mbps, SGMII interface, TX Disable function, with LOS function
ATRG-CH00-SC0LS-xx	Copper SFP 1000Mbps only, SERDES interface, TX Disable function, with LOS function

RAYCORE

Raycore is a fiber optic product brand name of Melbye Skandinavia AS. This Specification is subject to change without notice. Please visit our website www.melbye.com.tw for most update information and specification. Copyright © 2012 Melbye Raycore Taiwan Co., Ltd. All rights reserved.

